

GROUP 5®

G100 Family 100A 125V Stage Pin Wiring Instructions

- Use #2 or #4 Type SC single conductor cable (grounding wire can be #6 minimum), or use 4/3 or 6/3 Type W multiconductor cable.
 - When using Type SC cable, use gaffers tape to secure the three wires together in a bundle where they pass through the housing at the strain relief.
 - For applications needing 4/3 S-jacketed cable, use G100M-DB or G100F-DB which have a wider jacket opening.
 - Strip the conductors 3/4".
 - Two versions of wire termination are available.
1. Slide wire shoe (ferrule) over each wire and insert into appropriate terminal pocket.
 - Green wire into terminal marked "G"
 - White wire into terminal marked "N"
 - Black wire into terminal marked "H"
 - Tighten ¼"-28 double set screws to 30 in-lbs torque with 5/32" hex (allen) head wrench.
 2. Crimp a #4 ring terminal onto white and black wires.
 - Crimp a #6 ring terminal onto green wire.
 - Green wire to terminal marked "G"
 - White wire to terminal marked "N"
 - Black wire to terminal marked "H"
 - Place washer over ring terminal.
 - Attach to the appropriate terminal with the ¼"-20 terminal screw at 30 in-lbs torque.
- Place cover over housing and tighten the three ¼"-20 flat head screws to 14 in-lbs. torque.
 - Device is now ready for use.

GROUP 5®

G100 Family 100A 125V Stage Pin Wiring Instructions

- Use #2 or #4 Type SC single conductor cable (grounding wire can be #6 minimum), or use 4/3 or 6/3 Type W multiconductor cable.
 - When using Type SC cable, use gaffers tape to secure the three wires together in a bundle where they pass through the housing at the strain relief.
 - For applications needing 4/3 S-jacketed cable, use G100M-DB or G100F-DB which have a wider jacket opening.
 - Strip the conductors 3/4".
 - Two versions of wire termination are available.
1. Slide wire shoe (ferrule) over each wire and insert into appropriate terminal pocket.
 - Green wire into terminal marked "G"
 - White wire into terminal marked "N"
 - Black wire into terminal marked "H"
 - Tighten ¼"-28 double set screws to 30 in-lbs torque with 5/32" hex (allen) head wrench.
 2. Crimp a #4 ring terminal onto white and black wires.
 - Crimp a #6 ring terminal onto green wire.
 - Green wire to terminal marked "G"
 - White wire to terminal marked "N"
 - Black wire to terminal marked "H"
 - Place washer over ring terminal.
 - Attach to the appropriate terminal with the ¼"-20 terminal screw at 30 in-lbs torque.
- Place cover over housing and tighten the three ¼"-20 flat head screws to 14 in-lbs. torque.
 - Device is now ready for use.

GROUP 5®

G100 Family 100A 125V Stage Pin Wiring Instructions

- Use #2 or #4 Type SC single conductor cable (grounding wire can be #6 minimum), or use 4/3 or 6/3 Type W multiconductor cable.
 - When using Type SC cable, use gaffers tape to secure the three wires together in a bundle where they pass through the housing at the strain relief.
 - For applications needing 4/3 S-jacketed cable, use G100M-DB or G100F-DB which have a wider jacket opening.
 - Strip the conductors 3/4".
 - Two versions of wire termination are available.
1. Slide wire shoe (ferrule) over each wire and insert into appropriate terminal pocket.
 - Green wire into terminal marked "G"
 - White wire into terminal marked "N"
 - Black wire into terminal marked "H"
 - Tighten ¼"-28 double set screws to 30 in-lbs torque with 5/32" hex (allen) head wrench.
 2. Crimp a #4 ring terminal onto white and black wires.
 - Crimp a #6 ring terminal onto green wire.
 - Green wire to terminal marked "G"
 - White wire to terminal marked "N"
 - Black wire to terminal marked "H"
 - Place washer over ring terminal.
 - Attach to the appropriate terminal with the ¼"-20 terminal screw at 30 in-lbs torque.
- Place cover over housing and tighten the three ¼"-20 flat head screws to 14 in-lbs. torque.
 - Device is now ready for use.

MARINCO

marinco.com
Tech Support and Customer Service
800.307.6702

PN 202659 0315

MARINCO

marinco.com
Tech Support and Customer Service
800.307.6702

PN 202659 0315

MARINCO

marinco.com
Tech Support and Customer Service
800.307.6702

PN 202659 0315