

CAMLOCK CONNECTION SWITCH

POWER DISTRIBUTION

Power Assemblies' line of camlock disconnects offers a cost-effective solution for quickly and safely connecting cables along with switching capabilities with or without overcurrent protection. These units are wall mountable from 100A-1200A and pad-mounted from 1200A-3000A. They come in single or double throw configurations and are available in NEMA3R as a standard. Options include fusible or non-fusible switches, switched or non-switched neutrals, and source or load camlocks.

APPLICATIONS

- Temporary Power
- Portable Power
- Generator Connections

BENEFITS

- Quick Connections
- UL Listed Safety Switches
- Wide Configuration Range
- Outdoor Rated



 **SERIES 16 QUICK CONNECT**



SINGLE-THROW OR DOUBLE-THROW



FUSIBLE OR NON-FUSIBLE

** FUSES NOT INCLUDED

CAMLOCK CONNECTION SWITCH - PART NUMBER SCHEMA

CCS PRODUCT PREFIX	XX AMPERAGE	X THROW	X FUSE	X NEUTRAL	X CAM WIRING	X VOLTAGE CODE
01	100A	S Single-Throw	F Fusible	X None	S Source	1 120V (BLK/WHT/GRN)
02	200A	D Double-Throw	N Non-Fusible	S Switched	L Load	2 120/240V (BLK/RED/WHT/GRN)
04	400A			N Non-Switched (Solid)		3 208V (BLK/RED/BLU/GRN)
08	800A					4 120/208V (BLK/RED/BLU/WHT/GRN)
10	1000A					5 480V (BRN/ORG/YEL/GRN)
12	1200A					6 277/480V (BRN/ORG/YEL/WHT/GRN)
16	1600A					7 600V (RED/BLK/BLU/GRN)
20	2000A					8 347/600V (RED/BLK/BLUE/WHT/GRN)
25	2500A					
30	3000A					