

# QUICK CONNECT SWITCH

## POWER DISTRIBUTION

Power Assemblies' line of Quick Connect Switches offers a low-cost power solution that guarantees a particular electrical circuit is de-energized in case of an emergency stoppage, service, or maintenance. These units are NEMA3R and wall-mountable as a standard. Configurations range from 100A-1200A. Options include fusible or non-fusible switching mechanisms, switched or non-switched neutrals, and source or load camlocks.

### APPLICATIONS

- Temporary Power
- Portable Power
- Generator Connections

### BENEFITS

- Quick Connections
- UL Listed Switching Mechanisms
- Wide Configuration Range
- Outdoor Rated



SERIES 16 QUICK CONNECT



SINGLE-THROW



FUSIBLE OR NON-FUSIBLE

\*\* FUSES NOT INCLUDED

### QUICK CONNECT SWITCH - PART NUMBER SCHEMA

QCS PRODUCT PREFIX	XX AMPERAGE	X FUSE	X NEUTRAL	X CAM WIRING	X VOLTAGE CODE
01	100A	F Fusible	X None	X None	1 120V (BLK/WHT/GRN)
02	200A	N Non-Fusible	S Switched	S Source	2 120/240V (BLK/RED/WHT/GRN)
04	400A		N Non-Switched (Solid)	L Load	3 208V (BLK/RED/BLU/GRN)
08	800A			A All	4 120/208V (BLK/RED/BLU/WHT/GRN)
10	1000A				5 480V (BRN/ORG/YEL/GRN)
12	1200A				6 277/480V (BRN/ORG/YEL/WHT/GRN)
					7 600V (RED/BLK/BLU/GRN)
					8 347/600V (RED/BLK/BLUE/WHT/GRN)